

# surgeassure™

## INTERIOR SURGE PROTECTOR

### SAP1



### FEATURES & BENEFITS

- UL listed surge protection
- Rated for 120VAC 15A, grounded outlets
- Easy to install for homeowner for individual or multiple appliances
- Visual indication of “Protected” & “Grounded” status
- Multiple outlet taps have mounting screw
- Lifetime Product Warranty

The surgeassure™ SAP1 is a space saving wall plug protector designed for applications where a plug strip is not practical.

The SAP1 is ideal for answering machines, fax machines and any 120 volt appliance such as refrigerators, washing machines, microwave ovens and garage door openers.

Major household electrical and electronic equipment are covered against surge damage for Lifetime during ownership by the original purchaser when a surgeassure™ Wall Plug Interior Zone Protector is installed and when surgeassure™ Main Zone Protectors are installed.

If the SAP1 surge protector is damaged during the warranty period surgeassure™ will replace it free of Charge!

### TECHNICAL SPECIFICATIONS

AC SURGE PROTECTION	SAP1
Surge Capacity	36,000 Amps
Line Voltage	120 VAC
Protected AC Outlets	1
Phone Lines Protected	N/A
Coax Line Protected	N/A
Patch Cord Provided	N/A
EMI/RFI Filtering	Yes

### AGENCY APPROVALS & WARRANTY

UL Listings	1449 UL 498, UL 497A
UL 1449 Rating	400V
Product Warranty	Lifetime
*Connected Equipment Warranty	Lifetime (See warranty for details)

\*Requires all 3 surgeassure™ Main Zone Protectors to be installed at the home's incoming service.



SA Series Main Zone Protector



SATH2



SAVFFF

### SELECTION INFORMATION

CATALOG #	DESCRIPTION
SAP1	1 Outlet Wall Plug

### INSTALLATION INSTRUCTIONS:

**DO NOT INSTALL DURING ACTIVE STORM CONDITIONS.**

- 1) If the surgeassure™ protector has a mounting screw, remove the center screw of the receptacle.
- 2) Plug the protector into the receptacle and secure with the mounting screw.
- 3) Connect the equipment cord(s) into the AC receptacles of the protector.